

# RPN Keyboard Commands v1.1

CALCULATOR				
Keyboard	RPN-45	RPN-65	RPN-67	RPN-97
?	Calculator Keys	Help (Calculator)	Help (Calculator)	Help (Calculator)
^ ?	Calculator Keys	Help (Card Manager)	Help (Card Manager)	Help (Card Manager)
⇧ ⌘ I	Info	Info	Info	Info
⇧ ⌘ K	Stack Display	Stack Display	Stack Display	
<i>Discoverable Commands (hold ⌘ to reveal)</i>				
⌘ ?	Calculator Keys	Calculator Keys	Calculator Keys	Calculator Keys
⌘ S	Settings	Settings	Settings	Settings
⇧ ⌘ S	Toggle Separators	Toggle Separators	Toggle Separators	Toggle Separators
⌘ R	Registers	Registers	Registers	Registers
⌘ W	View	View	View	View
⌘ I	Info	Instructions	Instructions	Instructions
⌘ L		Listing	Listing	Listing
⌘ J	Complex Mode		Complex Mode	Complex Mode
⌘ P	Show/Hide Printer	W/PRGM-RUN	W/PRGM-RUN	PRGM-RUN
⌘ K	Stack Display	Stack Display	CC	CC
⌘ O			OP	OP
⌘ T	TXT	TXT	TXT	TXT
⇧ ⌘ T	Timer Mode on/off		TEXT Helper	TEXT Helper
⌘ M	Manual (Ref. Guide)	Card Manager	Card Manager	Card Manager
<i>Other Commands</i>				
⇧ ^ \ O	OFF/ON	OFF/ON	OFF/ON	OFF/ON
⇧ ^ \ N	Reset Calculator	New Program	New Program	New Program
⇧ \ N		Clear Program	Clear Program	Clear Program
⇧ ^ \ S	STO registers in backup			
⇧ ^ \ R	RCL registers from backup			
⇧ ^ \ <	Exchange registers with backup			
⇧ ⌘	Erase Paper	Erase Paper	Erase Paper	Erase Paper
⌘	CLx	CLx	CLx	CLx
\ ⌘	CLR A	DEL	DEL	DEL
^ \ ⌘	CLR A	Clear Stack & Main Regs	Clear Stack & Main Regs	Clear Stack & Main Regs

## RPN Keyboard Commands v1.1

CALCULATOR				
Keyboard	RPN-45	RPN-65	RPN-67	RPN-97
⇧ ^ \ ☒	CLR A	Clear Stack & All Regs	Clear Stack & All Regs	Clear Stack & All Regs
⇧ ^ S	Share	Share	Share	Share
^ ↵	Dismiss Share	Dismiss Share	Dismiss Share	Dismiss Share
⇧ ^ ↵	Dismiss Share	Dismiss Share	Dismiss Share	Dismiss Share
^ Tab		Eject Card	Eject Card	Eject Card
^ A...E		A...E	A...E	A...E
⇧ ^ A...E		a...e	a...e	a...e
▶	Gold → Purple → none	f → f <sup>1</sup> → g → none	f → g → h → none	f → EXT → none
◀	Purple → Gold → none	g → f <sup>1</sup> → f → none	h → g → f → none	EXT → f → none
▲	R↑	R↑	R↑	R↑
▼	R↓	R↓	R↓	R↓
\ ▲		BST	BST	BST
\ ▼		SST	SST	SST
⇧ ▲	Papertape top	Papertape top	Papertape top	Papertape top
⇧ ▼	Papertape bottom	Papertape bottom	Papertape bottom	Papertape bottom
^ ▲		Program top	Program top	Program top
^ ▼		Program bottom	Program bottom	Program bottom
^ ◀		Previous Label	Previous Label	Previous Label
^ ▶		Next Label	Next Label	Next Label
>	Swap Regs R0...R9	Swap R0..9 & RA..e	P≧S	P≧S
<	x≧y	x≧y	x≧y	x≧y
↵	ENTER	ENTER	ENTER	ENTER
A	ABS	ABS	ABS	ABS
C	CHS	CHS	CHS	CHS
E	EEX	EEX	EEX	EEX
F	Gold	f	f	f
⇧ F	Purple	f <sup>1</sup>	g	EXT
G	Purple	g	g	EXT
H	HYP		h	HYP
⇧ H	HYP		HYP	HYP
⇧ L	LN (also without ⇧)	LN	LN	LN
⇧ ^ L	LOG (also without ⇧)	LOG	LOG	LOG

## RPN Keyboard Commands v1.1

CALCULATOR				
Keyboard	RPN-45	RPN-65	RPN-67	RPN-97
<b>M</b>	→D.MS	→D.MS	H→H.MS	→H.MS
<b>⇧ M</b>	D.MS→	D.MS→	H.MS→H	H.MS→
<b>N</b>	n!	RTN	RTN	RTN
<b>R</b>	RCL	RCL	RCL	RCL
<b>S</b>	STO	STO	STO	STO
<b>X</b>	e <sup>x</sup>	e <sup>x</sup>	e <sup>x</sup>	e <sup>x</sup>
<b>^ X</b>	10 <sup>x</sup>	10 <sup>x</sup>	10 <sup>x</sup>	10 <sup>x</sup>
<b>Y</b>	y <sup>x</sup>	y <sup>x</sup>	y <sup>x</sup>	y <sup>x</sup>
<b>U</b>	→P	→P	→P	→P
<b>V</b>	→R	→R	→R	→R
<b>T</b>	Set Time	GTO	GTO	GTO
<b>Tab</b>	R/S (Timer)	R/S	R/S	R/S
<b>⌵ Tab</b>			PAUSE	PAUSE
<b>P</b>	Print x	Print x	Print x	Print x
<b>Space</b>	Paper Feed	Paper Feed	Paper Feed	Paper Feed
<b>⇧ Space</b>	Print Space	Print Space	Print Space	Print Space
<b>⇧ R</b>	Print Registers	Print Registers	Print Registers	Print Registers
<b>⇧ S</b>	Print Stack	Print Stack	Print Stack	Print Stack
<b>⇧ K</b>	Stack Display	Stack Display	Stack Display	Toggle Registers
<b>⇧ B</b>		Print Labels & Flags	Print Labels & Flags	Print Labels & Flags
<b>⇧ P</b>		Print Program	Print Program	Print Program
<b>⇧ ^ P</b>		Print Prog from Top	Print Prog from Top	Print Prog from Top
<b>^L or L</b>		LBL	LBL	LBL
<b>⌵ ^ L</b>			LBL f	
<b>^G or B</b>		GSB	GSB	GSB
<b>⌵ ^ G or ⌵ B</b>			GSB f	
<b>⌵ G</b>		GTO .	GTO .	GTO .
<b>⌵ L</b>	Last X	Last X	Last X	Last X
<b>⌵ P</b>	π	π	π	π
<b>⌵ S</b>	SIN	SIN	SIN	SIN
<b>⌵ C</b>	COS	COS	COS	COS
<b>⌵ T</b>	TAN	TAN	TAN	TAN

## RPN Keyboard Commands v1.1

CALCULATOR				
Keyboard	RPN-45	RPN-65	RPN-67	RPN-97
<b>^ I</b>	<b>INT</b>	<b>INT</b>	<b>(i)</b>	<b>(i)</b>
<b>⇧ I</b>	<b>FRAC</b>	<b>FRAC</b>	<b>RC I</b>	<b>I</b>
<b>^ \ I</b>	<b>Info</b>	<b>DSZ</b>	<b>DSZ (i)</b>	<b>DSZ (i)</b>
<b>⇧ ^ \ I</b>		<b>DSZ</b>	<b>DSZ</b>	<b>DSZ I</b>
<b>^ \ ⌘ I</b>			<b>ISZ (i)</b>	<b>ISZ (i)</b>
<b>⇧ \ ⌘ I</b>			<b>ISZ</b>	<b>ISZ I</b>
<b>I</b>	<b>1/x</b>	<b>1/x</b>	<b>1/x</b>	<b>1/x</b>
<b>Q</b>	<b>x<sup>2</sup></b>	<b>x<sup>2</sup></b>	<b>x<sup>2</sup></b>	<b>x<sup>2</sup></b>
<b>O</b>	<b>√x</b>	<b>√x</b>	<b>√x</b>	<b>√x</b>
<b>%</b>	<b>%</b>	<b>%</b>	<b>%</b>	<b>%</b>
<b>\ %</b>	<b>Δ%</b>	<b>% CH</b>	<b>% CH</b>	<b>% CH</b>
<b>D</b>	<b>Δ%</b>	<b>DSP</b>	<b>DSP</b>	<b>DSP</b>
<b>\$</b>	<b>Σ+</b>	<b>ABS</b>	<b>Σ+</b>	<b>Σ+</b>
<b>^ \$</b>	<b>Σ-</b>	<b>NOP</b>	<b>Σ-</b>	<b>Σ-</b>
<b>^ 1 / 2 / 3</b>	<b>Ribbon blk / blu / grn</b>	<b>Ribbon blk / blu / grn</b>	<b>Ribbon blk / blu / grn</b>	<b>Ribbon blk / blu / grn</b>
<b>^ P</b>	<b>Paper Mode</b>	<b>Paper Mode</b>	<b>Paper Mode</b>	<b>Paper Mode</b>
<b>^ M</b>	<b>MAN</b>	<b>MAN</b>	<b>MAN</b>	<b>MAN</b>
<b>^ T</b>	<b>TRACE</b>	<b>TRACE</b>	<b>TRACE</b>	<b>TRACE</b>
<b>^ N</b>	<b>NORM</b>	<b>NORM</b>	<b>NORM</b>	<b>NORM</b>
<b>^ S</b>	<b>Print Stack</b>	<b>Step Display on/off</b>	<b>Step Display on/off</b>	<b>Step Display on/off</b>
<b>^ \ F</b>	<b>FIX</b>	<b>DSP .</b>	<b>FIX</b>	<b>FIX</b>
<b>^ \ S</b>	<b>SCI</b>	<b>DSP</b>	<b>SCI</b>	<b>SCI</b>
<b>^ \ E</b>	<b>ENG</b>	<b>DSP +</b>	<b>ENG</b>	<b>ENG</b>

## RPN Keyboard Commands v1.1

CARD MANAGER		
Keyboard	RPN-65/67/97	Notes
⌘ ▲ or ▼	<b>Previous or Next Card</b>	Works on full list or search results
⌘ ◀ or ▶	<b>Previous or Next Category</b>	First card of current or previous category <i>or</i> First card of next category or last card of last category
⌘ ⌘ ▲ or ◀	<b>Top Card</b>	First card of first category
⌘ ⌘ ▶ or ▼	<b>Toggle Prog/Data Card</b>	Change from program to data cards, and vice versa
⌘ F	<b>Find Card</b>	<b>Tab:</b> changes search scope ↩ : selects first search result
⌘ ↩	<b>Select Card</b>	Ends search mode and selects card
⌘ C	<b>Back to Calculator</b>	
⌘ L	<b>Load Card</b>	Also <b>Merge Card</b> (RPN-67/97)
⌘ W	<b>Write Card</b>	
⌘ D	<b>Edit Description</b>	Automatically unprotects card
⌘ P	<b>Edit Program or Registers</b>	<b>RUN:</b> Automatically unprotects card <b>W/PRGM:</b> Shows card or calculator content
⌘ I	<b>Edit Instructions or Notes</b>	Automatically unprotects card
⌘ ⌘ P	<b>Protect or Content</b>	<b>RUN:</b> Toggles card protection on/off <b>W/PRGM:</b> Shows card or calculator content
⌘ ?	<b>Keyboard Commands</b>	Show/hide list of <b>card detail commands</b> in <i>Instructions</i>

## RPN Keyboard Commands v1.1

TEXT Helper		
⌘ C	<b>Back to Calculator</b>	
⌘ S	<b>Quit &amp; Insert <i>or</i> Replace Text</b>	Stores text after defined step value
⌘ T	<b>Edit Text</b>	Start entering free text
⌘ ◀ <i>or</i> ▶	<b>Previous <i>or</i> Next Alignment</b>	
⌘ R	<b>First Register</b>	Allows entering start register value
⌘ F	<b>Fetch Text</b>	Gets existing text at start register
⌘ I	<b>Insert <i>or</i> Replace Code</b>	Allows entering step value
⌘ M	<b>Mode</b>	Toggles Insert/Replace mode
⌘ N	<b>Numeric Character</b>	Allows entering character value
⌘ U	<b>Use Character</b>	Adds character defined by value to text
⌘ L	<b>List of Characters</b>	Displays list of character values
⌘ I	<b>Edit Instructions <i>or</i> Notes</b>	Automatically unprotects card
⌘ P	<b>PLOT C Position</b>	Allows entering line position for PLOT C command
⌘ O	<b>OP TEXT</b>	Adds or removes OP TEXT code

# RPN Keyboard Commands v1.1

## OFTEN-USED COMMANDS (RPN-65/67/97)

Command	Keys	Notes
New Program	⇧ ^ ⌘ N	Turns calc on, ejects card, sets W/PRGM mode, clears program memory
Clear Program	⇧ ⌘ N	Sets W/PRGM mode, clears program memory
LBL A	^ L A	Hold <b>control</b> key depressed, then type <b>L A</b>
LBA a	^ L ⇧ A	Press <b>control</b> , type <b>L</b> , add <b>shift</b> , type <b>A</b> (RPN-65 and -97 only)
	^ ⌘ L ^ A	Press <b>control &amp; option</b> , type <b>L</b> , release <b>option</b> , type <b>A</b> (RPN-67 only)
GSB C	^ C	
	B ^ C	
GSB c	⇧ ^ C	(RPN-65, -67 and -97)
	B ⇧ ^ C	(RPN-65 and -97 only)
	⌘ B ^ C	(RPN-67 only)
LBL 1	L 1	
GSB 2	B 2	
GTO 3	T 3	
GTO.123	⌘ G 1 2 3	Go to step 123 (Press <b>option</b> , type <b>G</b> , release keys, type <b>1 2 3</b> )
RTN	N	
BST	⌘ ▲	
SST	⌘ ▼	
Prev Label	^ ◀	Works in both RUN and PRGM mode
Next Label	^ ▶	Works in both RUN and PRGM mode
Step 000	^ ▲	Also ⌘ G 0 0 0 (Press <b>option</b> , type <b>G</b> , release keys, type <b>0 0 0</b> )
Last Step	^ ▼	Also ⌘ G . (Press <b>option</b> , type <b>G</b> , release keys, type decimal point)

### NOTES

- If some keys don't work as expected: make sure the **language** of the keyboard and the iPad match (press globe key left of the control-key to change)
- **Common shortcuts** are also available:
  - ⌘ C      Copy
  - ⌘ X      Cut
  - ⌘ V      Paste
  - ⌘ . or Esc    Cancel
- ☒ = delete, ↵ = return